國立臺灣大學 105 學年度碩士班招生考試試題

題號: 353 科目:自動控制

題號: 353


節次: 2 頁之第 共 頁

1. Consider the inverted pendulum system shown in Fig. 1. Assume that the mass of the inverted pendulum is m and is evenly distributed along the length of the rod. (The center of gravity of the pendulum is located at the center of the rod.) Assuming that θ is small, (1) derive mathematical models for the system in the forms of differential equations, (2) transfer functions, i.e., X(s)/U(s) and $\Theta(s)/U(s)$, and (3) state-space equations. Use the state vector $\mathbf{x} = [\theta, \theta', x, x']^T$. 【計分:20分】

Fig. 1

請於答案卷上作答,於試題卷上作答者,不予計分。

2. Consider the closed-loop system shown in Fig. 2. Determine the range of K for stability. Assume that K > 0.【計分:10 分】



3. Consider the following state equation and output equation:

$$\begin{bmatrix} \dot{x}_1 \\ \dot{x}_2 \\ \dot{x}_3 \end{bmatrix} = \begin{bmatrix} -6 & 1 & 0 \\ -11 & 0 & 1 \\ -6 & 0 & 0 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \\ x_3 \end{bmatrix} + \begin{bmatrix} 2 \\ 6 \\ 2 \end{bmatrix} u; \quad y = \begin{bmatrix} 1 & 0 & 0 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \\ x_3 \end{bmatrix}$$

Show that the state equation can be transformed into the following form by use of a proper transformation matrix:

$$\begin{bmatrix} \dot{z}_1 \\ \dot{z}_2 \\ \dot{z}_3 \end{bmatrix} = \begin{bmatrix} 0 & 0 & -6 \\ 1 & 0 & -11 \\ 0 & 1 & -6 \end{bmatrix} \begin{bmatrix} z_1 \\ z_2 \\ z_3 \end{bmatrix} + \begin{bmatrix} 1 \\ 0 \\ 0 \end{bmatrix} u$$

Then obtain the output y in terms of z_1 , z_2 , and z_3 . 【計分: 20 分】

4. Given a linear input/output system: $\frac{dx}{dt} = Ax + Bu$, y = Cx + Du,

where
$$A = \begin{bmatrix} -4 & 2 \\ -2 & -1 \end{bmatrix}, B = \begin{bmatrix} 0 \\ 2 \end{bmatrix}, C = \begin{bmatrix} 0 & 1 \end{bmatrix}, D = 0$$

Please find the rising time, overshoot and the steady state error of the system output for a unit step input [] 分:15分】

5. Plot the root locus for the system in the figure below. 【計分:7分】 Using the root locus, please determine the gain K so that the rising time of the output response of the system is less than 0.1sec. 【計分:8分】




Figure for problem 5.

6. if the open loop transfer function $KG(s) = \frac{1}{s(s+1)^2}$ (1) Please plot the Bode magnitude and phase for the open loop system and find the phase margin and gain margin 【計分: 10 分】(2) Please plot the Nyquist plot of the open loop system and discuss the stability of the close loop system. 【計分:10分】




Figure for problem 6.

試題隨卷繳回